

DIGITAL CLAMP METER M266F

APPLICATION: This is a 3½ Digits Multirange Clamp Meter with Backlight. This instrument can be used to measure AC/DC Voltage, AC Current, Resistance, Frequency, Continuity Test, and other parameters. It is an ideal tool for the Electricians, Engineers, Factories, Industries, Laboratories, Students, Household.

FEATURES:

- Display: 3½ Digits with 1999 Counts.
- Data Hold Function all Ranges
- Low Battery Indications
- Overload protection
- Over Range Indication
- Power supply: 9Volt battery
- Clamp Jaw Opening: 51mm.
- Reading Rate: 3 Times/second
- Operating Temperature & Humidity: 0°C To 50°C, <80%RH
- Storage Temperature & Humidity: -20°C To 60°C, <80%RH
- Display Size: 52 x 24mm
- Unit Size: 230×90×34mm
- Weight: 290gm Including Batteries
- Accessories: Instruction Manual, 1 Set Test Leads, 9 Volt Batteries, Carrying Cover.



SPECIFICATION:

Basic Function	Range	Best Accuracy
AC Current	200A/1000A (2 Ranges)	±2%
AC Voltage	750V (Auto Range)	±1%
DC Voltage	1000V (Auto Range)	±0.8%
Resistance	200Ω/20kΩ (2 Ranges)	±1%
Frequency	100kHz (Auto Ranges)	±1%
Continuity	Yes	